

Disassembly and assembly of gasoline Fengjun 5 generator

What is included in the manual for a gasoline generator?

The manual gives information with respect to operation and maintenance of the gasoline generator. Please read it carefully first before operating. If any trouble occurs, ask your local dealer who will provide you with the best after service. All the materials and diagrams of this manual coincide with the newest products at the publishing time.

How do I stop a generator set from running?

While the generator set is running, spray an engine fogger (such as OnaGard) into the carburetor, following the instructions on the container label. The engine fogger leaves a protective coat of oil on the internal surfaces of the engine. 4. Stop the generator set.

How do you stop a generator engine?

Start the generator and allow it to run until the generator engine stops. Push the Run/Stop switch to the Stop position. Remove the spark plug. Put a teaspoon of engine oil into the cylinder and pull the recoil handle until resistance is felt. At this position the piston is coming up on its compression stroke and both valves are closed.

What kind of fuel does a generator set engine use?

Gasoline Models: The engine is certified to operate on unleaded gasoline. LPG Models: The engine is certified to operate on LPG. See Section 5.6 on page 38 for fuel recommendations. See Section 5.5 on page 35 for engine oil recommendations. The generator set engines have precision-manufactured carburetors which are not adjustable. None.

How do you remove a generator from a genset?

Remove the generator/engine assembly from the genset, and then the engine, drive belt, exhaust manifold or ignition coils (magnetos) from the generator/engine assembly. Drain the engine oil because the genset will be turned on its side to remove components. Remove the two-piece control enclosure (Section 5).

How long should a new generator run on a rebuilt engine?

Proper engine break-in on a new generator set or on one with a rebuilt engine is essential for top engine performance and acceptable oil consumption. Run the generator set at approximately 1/2 rated power for the first 2 hours and at 3/4 rated power for 2 more hours.

Follow all safety information contained in this manual and on the generator. Symbol : Description : Safety Alert Symbol : Electrocution Hazard : ... Bad fuel, generator stored without treating or draining gasoline, or refueled with bad ...

Page 71: Section 5 Disassembly Disassembly Section 5 Major Disassembly Figure 5-2. Stepper Motor



Disassembly and assembly of gasoline Fengjun 5 generator

Harness Stator, Rotor, and Engine Removal Figure 5-11 Figure 5-12 for component location. Disconnect and remove the battery ...

The document is a user manual for a petrol generator that provides safety information and instructions for operation. It notes that the generator has been shipped without engine oil and ...



Disassembly and assembly of gasoline Fengjun 5 generator

Web: <https://www.ekusenitours.co.za>